

硬體話機設定說明

登入系統

台南市【教育網路中心】 - Microsoft Internet Explorer

檔案(F) 編輯(E) 檢視(V) 我的最愛(A) 工具(T) 說明(H)

網址(O) **http://163.26.xx.xx:9999** 移至 連結 台南市【教育網路中心】 台南市網路電話 網路管理

在此處輸入網址 **http://163.26.xx.xx:9999**
這是您網路電話機的IP

請選擇您的入口

輸入網路密碼

這個安全網站 (在 163.26.3.83) 要求您登入。
請輸入您在 VOIP 使用的使用者名稱與密碼。

使用者名稱(U)

密碼(P) **注意!!**
此處的密碼是您硬體電話的密碼

將這個密碼存到您的密碼清單(S)

確定 取消

教育局網站

活動連結

台灣燈會 Taiwan Lantern Festival 創造力學園

公告系統 電子郵件 學習護照 各級學校

■教育局 / 地址：台南市708永華路二段6號7樓 | 電話：(06) 2991111
■教育網路中心 / 地址：台南市700五妃街236-13號 [位置圖] | 電話：(06) 2130669 | 傳真：(06) 2130668 | 網站維護：✉

正在開啓網頁 http://163.26.3.83:9999/...

開始 網路電話 Microsoft PowerPoint - [...] 台南市【教育網路中心】...

網際網路 上午 08:54

系統主畫面

SIP IP Phone - Microsoft Internet Explorer

檔案(F) 編輯(E) 檢視(V) 我的最愛(A) 工具(T) 說明(H)

← 上一頁 → 搜尋 ★ 我的最愛

網址(D) http://163.26.3.83:9999/ 移至 連結 台南市【教育網路中心】 台南市網路電話 網路管理

Internet Telephony *IP PHONE* **IP PHONE**

Version: V.02.09
MAC Address: 00.D0.E9.01.7A.16

- Management
- Network Settings
- SIP Settings
- SIP Account Settings
- STUN & UPnP Settings
- Voice Settings
- Phone Settings
- Call Tracing Log
- Phone Book
- Speed Dial
- Line Key Settings
- Restart System

Web Login Setting	
User Name	aaaaa
Password <input type="button" value="Change"/>
Date/Time	
NTP Server IP	220.130.158.52
Time Zone	(GMT+08:00) Beijing, Singapore, Taipei
	<input type="checkbox"/> Daylight Saving
TFTP Server	
TFTP Server	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
FTP Client	
FTP Client	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Remote Config	
Remote Config Password

完成 開始 網路電話 Microsoft PowerPoint - [...] SIP IP Phone - Microsoft I... 網際網路 上午 08:59

修改SIP Settings

Step 1: 請點選這個連結，會出現右側的網頁

Step 2: 將Registrar Server的IP位置改成 163.26.2.3

Step 3: 將Outbound Proxy Server的IP位置改成 163.26.2.3

Step 4: 修改完需按下Submit

SIP Phone Setting	
SIP Phone Port Number	5060 [1024 - 65535]
Registrar Server	
Registrar Server Domain Name/IP Address	163.26.2.3
Registrar Server Port Number	5060
Authentication Expire Time	3600 sec. (Default: 3600 sec.) [60 - 9999]
Outbound Proxy Server	
Outbound Proxy Domain Name/IP Address	163.26.2.3
Outbound Proxy Port Number	5060
Others	
Session Timer	1800 sec. [90 - 99999]
Media Port	41000 [1024 - 65535]
Prack	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Session Refresher	<input checked="" type="radio"/> None <input type="radio"/> UAC <input type="radio"/> UAS
Session Timer Method	<input checked="" type="radio"/> Invite <input type="radio"/> Update
UDP/TCP	<input type="radio"/> UDP <input checked="" type="radio"/> TCP

修改SIP Account Settings

Internet Telephony *IP PHONE* IP PHONE

Version: V.02.09
MAC Address: 00.D0.E9.01.7A.16

- Management
- Network Settings
- SIP Settings
- SIP Account Settings** → 請點選這個連結，會出現右側的網頁
- STUN & UPnP Settings
- Voice Settings
- Phone Settings
- Call Tracing Log
- Phone Book
- Speed Dial
- Line Key Settings
- Restart System

SIP Account Setting	
Default Account	Account 1
Account 1 Setting	
Account Active	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Display Name	66666
SIP User Name	66666
Authentication User Name	66666
Authentication Password	12345678
Register Status	Register
Account 2 Setting	
Account Active	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Display Name	
SIP User Name	
Authentication User Name	
Authentication Password	
Register Status	UnRegister
Account 3 Setting	
Account Active	<input checked="" type="radio"/> Disable <input type="radio"/> Enable

完成 開始 網路電話 Microsoft PowerPoint - [...] SIP IP Phone - Microsoft I... 網際網路 上午 09:30

修改SIP Account Settings (Step2局部放大)

Account 1 Setting	
Account Active	<input type="radio"/> Disable <input checked="" type="radio"/> Enable
Display Name	66666 → 您的新網路電話號碼(五碼)
SIP User Name	66666 → 您的新網路電話號碼(五碼)
Authentication User Name	66666 → 您的新網路電話號碼(五碼)
Authentication Password	12345678 → 系統給您的新密碼(八碼)
Register Status	Register

修改SIP Account Settings

Internet Telephony *IP PHONE* IP PHONE

Version: V.02.09
MAC Address: 00.D0.E9.01.7A.16

- Management
- Network Settings
- SIP Settings
- SIP Account Settings**
- STUN & UPnP Settings
- Voice Settings
- Phone Settings
- Call Tracing Log
- Phone Book
- Speed Dial
- Line Key Settings
- Restart System

Authentication User Name	
Authentication Password	
Register Status	UnRegister
Account 3 Setting	
Account Active	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Display Name	
SIP User Name	
Authentication User Name	
Authentication Password	
Register Status	UnRegister
Account 4 Setting	
Account Active	<input checked="" type="radio"/> Disable <input type="radio"/> Enable
Display Name	
SIP User Name	
Authentication User Name	
Authentication Password	
Register Status	UnRegister

Step3: 將網頁向下拉

Submit ~~Reset~~ → 修改完請按下**Submit**

Restart System

SIP IP Phone - Microsoft Internet Explorer

檔案(F) 編輯(E) 檢視(V) 我的最愛(A) 工具(T) 說明(H)

← 上一頁 → 搜尋 ★ 我的最愛

網址(D) http://163.26.3.83:9999/default.htm 移至 連結 台南市【教育網路中心】 台南市網路電話 網路管理

Internet Telephony *IP PHONE* IP PHONE

Version: V.02.09
MAC Address: 00.D0.E9.01.7A.16

- Management
- Network Settings
- SIP Settings
- SIP Account Settings
- STUN & UPnP Settings
- Voice Settings
- Phone Settings
- Call Tracing Log
- Phone Book
- Speed Dial
- Line Key Settings
- Restart System**

Press [Restart] Button, IP Phone system will reboot!

→ **Step2:**
請按下Restart

Step1: 請點選這個連結，會出現右側的網頁

完成 開始 網路電話 Microsoft PowerPoint - [...] SIP IP Phone - Microsoft ... SIP Call Server管理系統... 網際網路 上午 09:51

Restart System

The screenshot shows a Microsoft Internet Explorer browser window displaying the SIP IP Phone management interface. The browser's address bar shows the URL `http://163.26.3.83:9999/`. The page header includes the text "Internet Telephony IP PHONE" and "Version: V.02.09" along with the "MAC Address: 00.D0.E9.01.7A.16". A navigation menu on the left lists various settings such as Management, Network Settings, SIP Settings, SIP Account Settings, STUN & UPnP Settings, Voice Settings, Phone Settings, Call Tracing Log, Phone Book, Speed Dial, Line Key Settings, and Restart System. The main content area contains the instruction "Press [Restart] Button, IP Phone system will reboot!" and a "Restart" button. A dialog box titled "Microsoft Internet Explorer" with the message "System Reboot?" is overlaid on the page, featuring two buttons: "確定" (OK) and "取消" (Cancel). A red box highlights the "確定" button, and a red arrow points from it to the Chinese text "按下確定" (Press OK) located below the dialog box. The Windows taskbar at the bottom shows the system tray with the time "下午 02:49" and several open applications including "網路電話安裝 (softph...", "網路電話 (hard phone...", and "SIP IP Phone - Micros...".

Restart System

SIP IP Phone - Microsoft Internet Explorer

檔案(F) 編輯(E) 檢視(V) 我的最愛(A) 工具(T) 說明(H)

← 上一頁 → 搜尋 我的最愛

網址(D) http://163.26.3.83:9999/ 移至 連結 Norton AntiVirus

Internet Telephony **IP PHONE** IP PHONE

Version: V.02.09
MAC Address: 00.D0.E9.01.7A.16

- Management
- Network Settings
- SIP Settings
- SIP Account Settings
- STUN & UPnP Settings
- Voice Settings
- Phone Settings
- Call Tracing Log
- Phone Book
- Speed Dial
- Line Key Settings
- Restart System

*System Rebooting
Please Wait...*

完成 網際網路

開始 網路電話安裝(softph... 網路電話(hard phone... SIP IP Phone - Micros... 下午 02:53

修改完成即可使用硬體電話